



VAN MEDEVOORT

CA360

CONTROL AMPLIFIER



Features:

- Six input, two channel control amplifier
- High slew rate for outstanding transient response
- Highly musical performance, low distortion
- Relay switching and muting circuitry
- Remote controlled inputs, volume and power
- With DC and RC output for switching power amps or sources
- Silver / black finished front plate

The Van Medevoort CA360 stereo pre-amplifier is built with very fast, low-distortion, discrete class 'A' line stages. This produces the highest quality musical performance for any type of music. The housing is extremely sturdy with a high quality silver / black finish. Only audiophile quality components are used. One gold plated XLR input is installed for an optimal connection with your DAC, CD- or Media player. Five RCA inputs are available to connect other sources and there are two pre-amp outputs. A remote output is fitted to switch the vM power amplifier on and off.

Specifications:

Amplifier channels	2
Input impedance	50 kOhms
Channel separation	> 100 dB / 1.5 -100,000 Hz
Distortion	< 0.002 % / 1.5 -100,000 Hz
Output impedance	< 100 Ohms
Output level nom.	1.5 Veff.
Gain	16 dB
Signal to noise ratio	> 100 dB
Inputs / connectors	6 / 1x XLR + 5x RCA
Outputs / connectors	2 / RCA
Power supply	115-230 Volt / 50-60 Hz
Power consumption	6/9 Watt standby/max
Weight	8.5 kg
Size w x h (h+feet) x d	434 x 88 (102) x 395 mm

Options: vM Silver Cable

Van Medevoort
Audio products

Visit our website for more information.
Copyright © 2015 Van Medevoort Audio / The Netherlands.
Specifications are subject to change without prior notice.

www.vanmedevoortaudio.nl
contact@vanmedevoortaudio.nl