



VAN MEDEVOORT

PA362

POWER AMPLIFIER



Features:

- 150 Watt stereo music power
- Handles any loudspeaker system including ESL
- Outstanding transient response through high slew rate
- Highly musical performance with low distortion
- XLR and RCA gold plated input connectors
- Protection circuitry and muting
- Remote controlled on / off by way of DC bus
- Silver / black finished front plate

The Van Medevoort PA362 stereo power amplifier is built with very fast, low-distortion, discrete class 'A' power stages and a more than generous power supply section. This produces top quality musical performance and best control over your loudspeaker system for any type of music. The housing is extremely sturdy with a nice silver / black finished front plate. Only audiophile quality components are used. A 12 Volt DC input is provided to switch the PA362 on and off with the remote control bus of your vM control amplifier.

Specifications:

Nominal power	> 2x 150 Watt / 8 Ohms
Damping factor	1200 - 1500
Input impedance	100 kOhms
Input level	1.5 Veff. / 150 Watt
Distortion	< 0.002 % / 1 -100,000 Hz >
Signal to noise ratio	106 dB
Inputs / connectors	2 / XLR + RCA switchable
Outputs / connectors	2 / 5 way binding posts
Power supply	115-230 Volt / 50-60 Hz
Power consumption	5/45-330 Watt stb/min-max
Weight	12 kg
Size w x h (h+feet) x d	434 x 88 (102) x 400 mm

Options: vM Silver Cable

Van Medevoort
Audio products

Visit our website for more information.
Copyright © 2015 Van Medevoort Audio / The Netherlands.
Specifications are subject to change without prior notice.

www.vanmedevoortaudio.nl
contact@vanmedevoortaudio.nl